AASKIN
Smart Life Simplified



DOT

OPERATING MANUAL

Kindly review the complete operating manual in detail before setting up the device

Universal Remote

Retrofit Design

Wi-Fi Inbuilt

App Control

Voice Control

SAFETY PRECAUTION AND PREREQUISITES

- Ensure that the steps mentioned in the installation guide are abided by throughout the installation process.
- Do not modify the device unless recommended by the technician sent by the manufacturer.
- Do not operate with wet or moist hands as it may cause electrocution.
- The device should be placed in a dry area, away from moisture & water.
- Turn off the power supply before connecting the Smart Remote device to the USB outlet.

ABOUT DOT

Smart Remote is a device that enables you to automate any remote of an appliance that is available with you. You will be able to create a universal remote with this device; hence you won't have to go through the hassle of finding the right remote to operate the appliance.

FEATURES

Retrofit Design: It can be plugged in any USB outlet, even the phone charger.
Robust Design: Advanced firmware and rugged hardware design for long-lasting performance.
Built-in S-Wi-Fi: Equipped with secure WiFi that controls appliances from anywhere.
Voice Command: The automation app is compatible with all types of voice assistants such as Alexa, Bixby, Google Assistant, Siri and more.
Universal Remote: You can add new remotes of various appliances to operate with your smart phone.

TECHNICAL SPECIFICATIONS

Power Input: 5 V DC (Mobile adapter)
Power Consumption: Max 2W
Number Of IRD LEDs: 4
IR Range: 15-20 M in line of sight
IR Coverage: 360°
Communication: Wi-Fi | Connects to 2.4 GHz, Wi-fi 802.11/b/g/n
Dimensions: Height- 44mm, Width - 40mm, Depth - 24mm

DEVICE SETUP

- Plug-in the smart remote in any USB socket or phone charger available in the room.
- Please note that electric fluctuations inside the switchboard may at times hinder optimal device performance.

CONFIGURE DOT TO THE MOBILE APP

It is mandatory to use a Wi-Fi router to configure the device.
If you are using mobile data, turn it off and switch to Wi-Fi.
Ensure that you are following the steps for configuration, in the same sequence, mentioned in the operating manual.

Step 1

- Download the APP.
- The app is available in Google Play and Apple's App Store.
- Create an account and log in.

Step 2

- Once logged in, set up your 'HOME' by clicking on the 'NEW HOME' button.
- If you have already created a 'HOME', skip to 'Step 3'.
- To create a home, pick a name and location and click on 'CREATE HOME'.
- There are two ways to provide 'HOME' access to your family members and relatives.
- 1. Go to SETTINGS > HOMES > MY HOME > USERS. When you tap on users, you get an option to add a user. Enter the email ID or phone number of the family member to Provide them with the access.
- 2. Ask your family members to 'JOIN HOME' when they are creating an account. It allows them to send you a request to add them as a user by entering your email ID or phone number. As a request arrives at your phone or email, you can provide them with access once approved.

Step 3

- To set-up switch device, go to SETTINGS > DEVICES
- Tap on the '+' button.
- Out of the products list, Select IR BLASTERS > SMART IR and tap on NEXT.

Step 4

- Ensure that the mobile data is disconnected.
- To connect your mobile phone to the device's hotspot, tap on the 'GO TO WI- FI SETTINGS' shown at the bottom of your mobile screen.
- Make sure that when you're connecting your device to your phone, the device must be set to reset mode (by default it will be in reset mode) i.e. The red light should be glowing.
- If not in reset mode, press and hold the reset button for 10 seconds. The red light will start glowing indicating that IR Blaster has been set to reset mode.
- Now find and select the device wi-fi – "ir_blaster_****, in the list of wi-fi network.
- Return to the app (NOTE: not by minimize button instead just press back), you will find options to connect to your home wi-fi from the app, select and enter the PASSWORD > CONFIRM PASSWORD and wait for the notification "CONFIGURATION DONE!", tap on NEXT.
- Now name your DEVICE AND ASSIGN TO ROOM > tap on CREATE DEVICE.
- You will receive a notification "SUCCESS".

CONTROLLING THE APPLIANCE

- To test the appliance and the switch, go to **'DEVICES'** in the app and click on your **'***Room'**, tap on **'SWITCH ON'** or the device name you created to test the device.
- Once you tap on the option, the device will start working, and the Icon of the button will turn yellow.
- At the bottom of the switch section, you can see the **'RUNNING TIME'** of the appliance, which allows you to check and manage your power accordingly.
- You can tap on the device icon multiple times to see if the device is working smoothly or not.

DELETING A DEVICE

- To remove the device from your list of devices.
- Go to **SETTINGS > DEVICES**, select the device you want to remove and at the bottom of the device information, you get an option to **'DELETE DEVICE'**.

FACTORY RESET

- To reset the device, toggle the switch on and off seven times within 7 seconds. This will remove the device Wi-Fi from your app.
- The Wi-Fi network of the device will be again visible in the list of available Wi-Fi networks.
- To reconfigure, you can follow the configuration steps from **'Step 3'** mentioned above.

DISCLAIMER

- In case the device is not working within the warranty period, and the user modified the product without prior notice, the device is not applicable under warranty services.

Devices labelled with this symbol should not be disposed of with other household wastes. It shall be handed over to the applicable collection point for the recycling of waste electrical and electronic equipment.

Works Well With

Alexa | Google Assistant | Siri | Google Home

Available on the App Store

GET IT ON Google Play

Designed By
AASKIN AUTOMATION PVT LTD
www.aaskin.in

Customer Support
Email: support@aaskin.in
Call: 0824 350 1133

Designed By Qapfy.com